



IC-A16E

VHF AIR BAND TRANSCEIVER

8.33/25 kHz Ground to Air Radio with Class Leading 1500 mW Powerful Audio









SPECIFICATIONS

	IC-A16E	
GENERAL		
Frequency range	TX/RX: 118.000-136.992 MHz	
Number of memory channels	200 channels	
Channel spacing	8.33 kHz*/25 kHz (* May differ depending on the countr	
Type of emission	6K80A3E, 5K00A3E	
Power supply requirement	7.2 V DC	
Current drain (approximate)		
TX High	1.8 A	
RX Max. audio/Stand-by	650 mA/65 mA typical	
Antenna impedance	50 Ω (BNC type antenna connector)	
Operating temperature range	-20°C to +55°C	
Dimensions (W×H×D) (Projections not included)	52.2 × 111.8 × 34.1 mm (with BP-280)	
Weight (approximate)	257 g (with BP-280)	
TRANSMITTER		
Output power (at 7.2 V DC)	6.0 W (PEP), 1.8 W (carrier)	
Audio harmonic distortion	Less than 10% (at 85% + 3 dB modulation)	
Harmonics spurious emissions	Less than –36 dBm (Except for operating frequency ±1 MHz.)	
Frequency stability	±1 ppm	
RECEIVER		
Intermediate frequencies	46.35 MHz (1st), 450 kHz (2nd)	
Sensitivity	Less than 0 dBµ (at 12 dB SINAD with CCITT)	
Squelch sensitivity (Threshold)	Less than 0 dBµ	
Spurious response	More than 70 dB	
Hum and noise	More than 40 dB (at 90% modulation)	
	1500 mW typical More than 350 mW (AM 8 Ω 60% modulation at 10% distortion)	
External speaker connector	3 conductor 3.5 (d) mm	
Measurements made in accorda	nce with EN300 676-2.	

Applicable U.S. Military Specifications

All stated specifications are subject to change without notice or obligation.

Standard	MIL 810G	
	Method	Procedure
Low Pressure	500.5	I, II
High Temperature	501.5	I, II
Low Temperature	502.5	I, II
Temperature Shock	503.5	I–C
Solar Radiation	505.5	I
Rain Blowing/Drip	506.5	I, III
Humidity	507.5	II
Salt Fog	509.5	-
Dust Blowing	510.5	I
Immersion	512.5	I
Vibration	514.6	I
Shock	516.6	I, IV

Also meets equivalent MIL-STD-810-C. -D. -E and -F.

Ingress Protection Standard	
Dust and Water	IP67/54


Supplied accessories: (* Not supplied, depending on the transceiver version.) ●BP-280 battery pack ●BC-213 rapid charger* ●BC-242 AC adapter* ●FA-B02AR antenna ●MB-133 belt clip ●Hand strap

OPTIONS

BATTERY PACKS

BP-278 Rechargeable Li-ion 7.2 V 1190 mAh (typ.), 1130 mAh (min.). BP-279 Rechargeable Li-ion 7.2 V

BP-280 Rechargeable Li-ion 7.2 V









▲BP-280

▲BP-278 ▲BP-279

DESKTOP CHARGER

BC-213 Charges the BP-278, BP-279 or BP-280. BC-242 AC adapter. Same as supplied. BC-123SE/SUK/SV* AC adapter.

* SE for Europe, SUK for UK, SV for Australia.





MULTI-CHARGER

BC-214* Charges up to six transceivers and/or batteries at the same time. BC-157S AC adapter.

* The AD-130 charger adapter is supplied with the BC-214, depending on the charger version.





VEHICLE CHARGER CABLE

CP-23L For use with the BC-213.





CHARGER BRACKET MB-130 For use with the BC-213.





Bluetooth® HEADSET

VS-3 With side tone function when connected to transceiver.





BELT CLIP MB-133

Same as supplied.





ANTENNA FA-B02AR Same as supplied.

SOFTWARE AND CABLE

www.icomjapan.com

CS-A16 Programming software for Windows® PC. OPC-478UC USB type radio programming cable.

lcom, lcom Inc. and lcom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand, and/or other countries. Windows is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Icom Inc. is under license. All other trademarks are the properties of their respective holders.

ICOM Inc. 1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icomamerica.com

www.icomcanada.com

E-mail: sales@icombrazil.com

Icom Canada

Icom Brazil

Icom America Inc. Icom (Europe) GmbH

www.icomeurope.com

Icom Spain S.L. www.icomspain.com

Icom (UK) Ltd. www.icomuk.co.uk

Icom France s.a.s. www.icom-france.com

Icom (Australia) Pty. Ltd. www.icom.net.au

Shanghai Icom Ltd. www.bjicom.com

Your local distributor/dealer:







Count on us!